

PRODUCT CATALOGUE



Intelligent wireless burglar alarm system

Model No.:ATS-401

Description:

DIY, Wireless installation Easy-to-operated. International famous chipset "2262" coding, advanced beaverboard, automatization producing pipelining, so the control panel is so stable with strong compatible function. It is integrated with home, business store, public plaza security and so on intelligent home function. Widely used for signal home, residential area, school, factory, electric power Dept. Oil Dept, oil Dept, railway Dept. CHy planning Dept. Police Dept.....all industrial security and protection system.

FEATURES:

1. Protection different zone: 32 zones with 32 different zones indicated on panel.
2. Each zone can be put more sensors.
3. Partial disarmed optional by remote control. One keypad easy to partial disarmed some sensors that programmed in the second zone.
4. Auto-dial up 6 phone numbers and recycle to repeat unless confirmed.
5. Store voice recorded message (10 second), it can be recovered. When received alarm message, it speaks as you spoken.
6. NI-MH rechargeable battery to back up power: >24 hours. Auto-switch if AC power is off.
7. Telephone manages the alarm system, convenience.
8. Phone trunks protected to avoid any designing destroy.
9. LED on the panel to display protection zone.
10. PIR detector is preset for the second zone which can be disarmed solely
11. Audible mute siren optional.
12. Quick program by the panel keyboard.
13. When received alarm call, you can press the keypad on the phone to disarm/arm/monitoring/start on/off siren
14. Panel keyboard password protected and incoming calling password protected.
15. Alarm time can be customized.
16. Siren sounds time/ Alarm triggered time/armed alarm times to be programmed to be delayed
17. All panels can connect with the alarm receipt managing centre

SPECIFICATION:

1. Wireless frequency: two option: 433MHz or 315MHz
2. An adaptor: option: input electricity from 110 ACV ~240 AC, customized. Adaptor choosing: two round pins, two flat pins, three pins customized
3. Wireless receiving distance in open place: >200m, indoor: 30~50m, (depend on the surrounding environment and wireless interference)
4. Standby current: < 20mA
5. Alarm volume: internal :95dB, external siren: 110~120 dB
6. One control panel with one internal siren: working voltage: +9 DCV, 200mA.
7. two wireless remote controllers: four button: disarm/arm/panic/PIR detector
8. One wireless magnetic door sensor: 12 DCV
9. One wireless infrared detector: 10m'120' horizontal+60'vertical
10. Optional sensor: wire siren, wireless smoke detector, gas leakage detector, vibration sensor, siren with strobe light, remote control, all sensors as we selling
11. Packing box: 31.5'25.8'7.5cm Carton(10sets):53'35'41cm.

Standard package: one control panel with internal siren, one magnetic door sensor, one PIR detector, two remote controllers, one telephone line, one adaptor, one instruction.